

LUMA LED Deck Light

Thank you for purchasing TACO LUMA LED lighting. The “Deck Light” comes complete with stainless steel mounting bracket, machine screw, and nut and washer to fasten to an existing mounting tab on your tower.

1. Pass the machine screw through the mounting bracket hole and mounting hole on the tower, then install the washer and nut. It is recommended that the washer furnished is used to prevent scoring the tower tab. Tighten the nut securely. When drilling a mounting hole in other locations, use a ¼" drill bit. If drilling stainless steel, the drill bit must be sharp. It is recommended that a 1/8" pilot hole is drilled first. *Hint: Keep the drill bit moist with a little motor oil to provide lubrication. Use a slow speed, while keeping pressure on the drill.*
2. Using the lead from the back of the fixture, connect to a power supply which is fused or on a circuit breaker. *The fixture only draws 0.26 amps, or less than one amp of power, so a 1 amp fuse or breaker is sufficient.*
3. **When making wiring connections, be absolutely certain that the white lead is connected to the positive side of the power supply; and the black lead is connected to ground. (12volt DC ONLY).** When using an in-line fuse, install the fuse in the positive supply side.
4. Aim the light fixture to maximize the amount of light where you want it and tighten the two fixing nuts, which lock the fixture head in desired position.